

## Update DALI Control 64 Gateway [SCN-DA64x.04]

The update can only be done via a FAT32 formatted microSD memory card (11x15mm).  
Use a memory card with at least 1 GB capacity.

### Preparation

First download the update for your DALI Control 64 Gateway from [www.mdt.de](http://www.mdt.de) and unpack the zip archive on your PC. The zip archive contains a .bin file corresponding to your gateway:

D1\_xxxx.bin → SCN-DA641.04

D2\_xxxx.bin → SCN-DA642.04

Now copy the .bin file into the root directory of the microSD card.

### Update



SCN-DA642.04

#### Note:

The microSD card slot is covered with a sticker when delivered. The slot is located to the right of the 230 V connection terminals. Remove the sticker for the update process and cover the slot again afterwards.

- Step 1: Switch off the 230 V mains voltage.
- Step 2: Insert the microSD card as shown.
- Step 3: Press and hold the programming button.
- Step 4: Switch on the 230 V mains voltage again. (Button remains pressed!)
- Step 5: The programming LED now starts to flash. Release the programming button and wait another 5 seconds.
- Step 6: Switch off the mains voltage again and remove the microSD card from the slot.
- Step 7: The update is now complete. Switch on the 230 V mains voltage again and put the gateway into operation via the ETS.

The updated firmware version can be verified via the device information of the ETS.